

Famoso 1000 RF



The Famoso RF is one of Grasslins' easiest programmable thermostats. From the moment you place the batteries into the programmer, you are guided step by step through the setup procedure. All items that are required will flash as you step through the setup. Simply adjust the value with the up or down button then press the ok button to continue to the next step.

In the example below we will guide you through setting the time, temperature and program the unit to bring the heating on at 21^o between the hours of 6am to 10am and 6pm to 11pm.

- 1, Place batteries into the programmer (if all ready fitted, press "reset" and "ok" together).
- 2, Hours will flash. Use + or - to adjust to current hour then press "ok".
- 3, Minutes flash. Use + or - to adjust minutes to current time then press "ok".
- 4, Marker under day flashes. Use + or - to move marker under current day (1=Mon) then press "ok"
- 5, Comfort temperature flashes (is preset at 21^o). Adjust using + or - buttons if required. Press "ok".
- 6, Setback (off) temperature flashes. Set this to 7^o using - button. Press "ok".

At this point you can select a preset program or select "PD" to program your own on/off times. Because we are creating a program with our own times we will select "PD".

- 7, P# will flash and marker under Monday. Use + or - to select PD then press "ok".
- 8, 0:00 will flash. This is the time for on/off.
- 9, Press the "-" button several times until you see 6:00.
- 10, Press "+" several times until you see 10:00.
- 11, Press "-" several times until you see 18:00.
- 12, Press "+" several times until you see 23:00.
- 13, Press "-" several times until you see 0:00.
- 14, Press "ok"

The program is now set and will turn the boiler on between 6am to 10am and 6pm to 11pm.

- 15, P# will flash and marker under Tuesday. Use + or - to select PD then press "ok" Twice.
- 16, P# will flash and marker under Wednesday. Use + or - to select PD then press "ok" Twice.
- 17, P# will flash and marker under Thursday. Use + or - to select PD then press "ok" Twice.
- 18, P# will flash and marker under Friday. Use + or - to select PD then press "ok" Twice.
- 19, P# will flash and marker under Saturday. Use + or - to select PD then press "ok" Twice.
- 20, P# will flash and marker under Sunday. Use + or - to select PD then press "ok" Twice.

The thermostat is now setup to turn the heating on between 6am to 10am and 6pm to 11pm seven days a week. The temperature is set at 21⁰C and the heating will hold the room at that temperature between those times. The off period is known as "Setback or economy". This is represented by the moon symbol.

As we have set the moon temperature to 7⁰, The heating will not come on unless the temperature falls below 7⁰C in the off period.

Your Famoso is now setup and ready to use.

This is just an example of how to program your own times and temperatures. If the room is not warm enough during the on periods, simply press the "ok" button several times until you see a "Sun" symbol and a temperature. Use the "+" or "-" buttons to adjust the temperature, then press "ok". Press the top button (Under sun) to return to default screen.

When the controller is in timed/auto mode you will see a "clock" and a "sun" (on) or "moon" (off) symbol. To scroll through the options use the top button (under sun).